

Device Maintenance

Battery Replacement

Materials:
Phillips Screwdriver
Replacement Battery (MN1300)

- Remove the cover from the device by unscrewing the four screws.

- Tip out the battery holder.

Note: Do not pull on the battery leads.

- Replace the 6 D-cell batteries and put the holder back into the device.

- Replace the cover taking care not to pinch the wires. Screw the enclosure back together securely.

Note: Be sure not to over tighten the screws or strip the threads.

Battery Warning

WARNING: FIRE, EXPLOSION, AND SEVERE BURN HAZARD. DO NOT SHORT CIRCUIT, CHARGE, FORCE OVER DISCHARGE, DISASSEMBLE, CRUSH, PENETRATE OR INCINERATE. BATTERY MAY LEAK OR EXPLODE IF HEATED ABOVE 54°C (129°F).

Recalibration

The Shock101-EB standard calibration is one point at 25°C, two points at 25%RH and 75%RH, two points at 15PSI and 27-30PSI and 0g for the x-axis, 0g for the y-axis and 7g for the z-axis.

Note: The shock parameters are not traceable to NIST.

Pricing:

Recalibration \$46.00

Additional:

As Found Data \$15.00 per channel

Non-NIST Traceable certificate \$30.00

To send the devices back, visit www.madgetech.com, select Services then RMA Process.

Part Number	Shock101-EB
Channels	Shock (3 axes)
Acceleration Range	
Acceleration Resolution	*See Table Below
Calibrated Accuracy	
Memory	349,525/axis
Reading Rate	64Hz up to 1 hour
Required Interface Package	IFC110 or IFC200
Baud Rate	115,200
Typical Battery Life	60 days
Operating Environment	-18 to +55°C, 0 to 95%RH (non-condensing)
Material	Anodized aluminum
Dimensions	5.5" x 5.2" x 3.2" (140mm x 132mm x 80mm)
Approvals	CE

*Shock101-EB Acceleration Range, Resolution and Accuracy

Range (g)	±5	±50	±100
Accuracy (g)	±0.2	±1	±2
Resolution (g)	0.01	0.05	0.1

Specifications subject to change.

See MadgeTech's terms and conditions at www.madgetech.com

MadgeTech, Inc.

PO Box 50 • Warner, NH 03278

Phone 603.456.2011 • Fax 603.456.2012

www.madgetech.com • info@madgetech.com



Shock101-EB-5

Tri-axial 5G, Shock Recorder with Extended Battery Life.

Shock101-EB-50

Tri-axial 50G, Shock Recorder with Extended Battery Life.

Shock101-EB-100

Tri-axial 100G, Shock Recorder with Extended Battery Life.

Shock101-EB-200


Tri-axial 200G, Shock Recorder with Extended Battery Life.

Product Notes

Reading Intervals

The Shock101-EB records peak acceleration levels for a specified reading interval. This means that the Shock101-EB will record the largest acceleration on each of the axes during each reading interval.

For Example:



Axis

When the Shock101-EB is laying flat with the label facing up, the x-axis is the one that reads left to right and will read around 0 when still. The y-axis reads top to bottom and will read around 0 when still. The z-axis reads perpendicular to the other two axis's, and will read around 1 when still.

Installation Guide

Installing the Interface cable


- IFC200, IFC202 or IFC300
Refer to the "Quick Start Guide" included in the package.
- IFC110, IFC102 or IFC103
Plug the serial cable into the port and verify it is secure.
- USB-1 or USB-101
Install the USB drivers from the CD provided in the kit, then plug the USB cable into the computer and the serial cable into the serial port.

Installing the software

Insert the Software CD in the CD-ROM Drive. If the autorun does not appear, locate the drive on the computer and double click on **Autorun.exe**. Follow the instructions provided in the Wizard.

Connecting the data logger

- Once the software is installed and running, plug the interface cable into the data logger.
- Click the **Communication Menu**, then **Auto Configure Port**.
- After a moment, a box similar to the following will appear;



- Click **OK**. The **Device Status** box will appear. Click **OK**.
- At this point, communications have been configured for your logger. These settings can be found under the **Communication Menu**.

Note: For additional installation instructions refer to your "Data Logger & Software Operating Manual".

Device Operation

Starting the data logger

- Click **Device Menu** then **Start Device**.
- Choose the desired start method.
- Choose the start parameters by selecting a **Reading Rate** suitable for your application.
- Enter in any other desired parameters and click **Start**.
- A box will appear stating the data logger has been started. Click **OK**.



- Disconnect the data logger from the interface cable and place it in the environment to measure.

Note: The device will stop recording data when the end of memory is reached or the device is stopped. At this point the device cannot be restarted until it has been re-armed by the computer.

Downloading data from a data logger

- Connect the data logger to the interface cable.
- Click the **Device Menu** then **Read Device Data**. This will offload all recorded data onto the PC.

Technical Support

Visit www.madgetech.com, or call (603) 456-2011. Technical support is also available by e-mailing support@madgetech.com

Additional product information is available by e-mailing info@madgetech.com.